

300W - 4000W 12V | 24V to 230V Car Inverter

- Charge any device (laptops, household electronics, TVs, etc.) on the go.
- Stable & safe conversion.
- Pure sine wave output.
- Built with high quality materials. Protective metallic case.
- Easy to store & transport.
- Digital display shows output voltage.
 (models: 500W, 1000W, 1500W, 2500W, 4000W)
- LED indicators for working / errors.
- Cables included.
- Additional output: 1x USB output.

Technical Specifications

Power	300 W	500 W	1000 W	1500 W	2500 W	4000 W
Peak Power	600 W	1000 W	2000 W	3000 W	5000 W	8000 W
Input Voltage	12 V		12 V	24 V	12 V	
Output Voltage	230V AC					
Output Frequency	50 Hz					
Outputs	1 x Schuko	2 x Schuko + 1 x USB				
Waveform	Pure Sine Wave					
Dimension LxWxH (mm)	210x115x63	270x151x85	325x165x92	390x167x90	415x165x82	467x200x154
Weight	0.92 kg	1.9 kg	3.2 kg	4.2 kg	7.2 kg	9.2 kg
Compatible Batteries	Any 12V batteries		Any 24V bat.	Any 12V batteries		

Models:



300W



500W



1000W | 1500W | 2500W



4000W

Due to continuous product improvements, program specifications are subject to change without notice

Address: Holland, City: Wassenaar, Dr. Mansveltkaade Street 48, Postal code: 2242XM